




# Piccolo Alert PCIe

PCIe video capture card with four BNC connectors for up to 16 standard PAL/NTSC cameras



## At a Glance

- 4x BNC connectors on the bracket, expandable to 16 with three [1203] VEB modules (sold separately)
- PCIe x1 bus
- Sixteen shared video decoders, 100/120 images per second (200/240 fields per second)
- Real-time acquisition from 4 cameras, fast switching between up to 16 cameras
- Independently-programmable frame rate and acquisition parameters for each video input

## Benefits

### Video input configurations

- Four cameras can be connected using the BNC connectors on the bracket: Acquisition at 30 (NTSC) or 25 (PAL) frames per second per camera
- Sixteen cameras can be connected using the BNC connectors on the bracket and three [1203] VEBs: Acquisition at 7.5 (NTSC) or 6.25 (PAL) frames per second per camera

### Windows drivers available

### Machine Vision for the General Manufacturing Industries

- Low cost image acquisition from industrial analog cameras for inspection machines

### Life Sciences & Medical

- Standard and high-definition image acquisition for endoscopy applications
- Standard and high-definition image acquisition for dental applications

### Microscopy

- High-definition image acquisition for offline inspection stations
- High-definition image acquisition for laboratory and measuring microscopes

### ITS (Intelligent Transportation System) & Traffic management

- Video acquisition from multiple cameras

## Specifications

### Mechanical

Form Factor	PCI Express card
Format	Standard profile, half length, 1-lane PCI Express card
Dimensions	L 167.65 mm x H 106.65 mm L 6.6 in x H 4.38 in

### Host bus

Standard	PCI Express 1.0
Link width	1 lane
Link speed	2.5 GT/s (PCIe 1.0)
DMA	32-bit
Peak delivery bandwidth	256 MB/s
Effective (sustained) delivery bandwidth	180 MB/s (Host PC motherboard dependent)
Power consumption	Max. 9.5 W (2.9 A @ +3.3 V)

### Camera / video inputs

Interface standard(s)	NTSC-M, PAL-B/G, RS-170, CCIR
Connectors	<ul style="list-style-type: none"><li>• VIDEO 1 to VIDEO 4: BNC female connectors on the bracket for composite video inputs</li><li>• VEB LINK 0 to VEB LINK 3: 10-pin shrouded header connectors on the PCB for VEB modules</li></ul>
Termination resistor	Selectable using switches on the bracket
Native resolution	Square pixels, broadcast and custom resolutions
Frame rate	<ul style="list-style-type: none"><li>• Up to 25/30 images per second, 50/60 fields per second per input</li><li>• Total 100/120 images per second with up to 16 cameras</li></ul>
Number of cameras	16
Number of cameras (at full frame rate)	4
Line-scan cameras supported	No

### Video delivery

Raw video format(s)	<ul style="list-style-type: none"><li>• Packed RGB color formats: RGB15, RGB16, RGB24, RGB32</li><li>• Planar RGB color formats: RGB24PL</li><li>• Packed YUV color formats: YUV411, YUV422, YUV444</li><li>• Planar YUV color formats: YUV411PL, YUV422PL, YUV444PL, YUV411PL, YUV422PL</li><li>• Monochrome formats: Y8</li></ul>
Deliverable video resolution (SD)	Frame, field, CIF, QCIF and custom image formats

### Area-scan camera control

Trigger	<ul style="list-style-type: none"><li>• Hardware trigger for up to four cameras</li><li>• With configurable noise removal filter and optional delay</li></ul>
Strobe	<ul style="list-style-type: none"><li>• Hardware strobe signal for up to four cameras</li><li>• With programmable position and duration</li></ul>

### General Purpose Inputs and Outputs

Number of lines	9 I/O lines: <ul style="list-style-type: none"><li>• 4 contact closure inputs (IN)</li><li>• 5 solid-state relay outputs (OUT)</li></ul>
-----------------	--

Connectors	I/O: 20-pin dual-row 0.1" shrouded header on the PCB
Usage	General purpose IO
Electrical specifications	<ul style="list-style-type: none"> <li>• IN: Polarity-free inputs, compatible with TTL, 12V and 24V signals, opto-couplers, relays and switches</li> <li>• OUT: Opto-isolated potential-free and polarity-free solid-state outputs, compatible with signals up to 30V, with 4 <math>\mu</math>s fall time, isolated up to 500V</li> </ul>
Watchdog	Yes

## Software

Host PC Operating System	<ul style="list-style-type: none"> <li>• Microsoft Windows 10, 8.1, 7 for x86 (32-bit) and x86-64 (64-bit) processor architectures</li> <li>• Linux for x86 (32-bit) and x86-64 (64-bit) processor architectures</li> </ul> <p>Refer to release notes for details</p>
APIs	<ul style="list-style-type: none"> <li>• MultiCam 32- and 64-bit binary libraries (Windows and Linux), for ISO-compliant C/C++ compilers</li> <li>• DirectShow 32- and 64-bit filters (Windows only), for Microsoft Visual C++ compilers</li> </ul>

## Environmental conditions

Operating ambient air temperature	0 to +50 °C / +32 to +122 °F
Operating ambient air humidity	10 to 90% RH non-condensing
Storage ambient air temperature	-20 to +70 °C / -4 to +158 °F
Storage ambient air humidity	10 to 90% RH non-condensing

## Certifications

Electromagnetic - EMC standards	<ul style="list-style-type: none"> <li>• European Council EMC Directive 2004/108/EC</li> <li>• United States FCC rule 47 CFR 15</li> </ul>
EMC - Emission	<ul style="list-style-type: none"> <li>• EN 55022:2010 Class B</li> <li>• FCC 47 Part 15 Class B</li> </ul>
EMC - Immunity	<ul style="list-style-type: none"> <li>• EN 55024:2010 Class B</li> <li>• EN 61000-4-2</li> <li>• EN 61000-4-3</li> <li>• EN 61000-4-5</li> <li>• EN 61000-4-6</li> </ul>
KC Certification	Korean Radio Waves Act, Article 58-2, Clause 3
Flammability	PCB compliant with UL 94 V-0
RoHS	European Union Directive 2011/65/EU (ROHS2)
REACH	European Union Regulation 1907/2006
WEEE	Must be disposed of separately from normal household waste and must be recycled according to local regulations

## Ordering Information

Product code - Description	<ul style="list-style-type: none"> <li>• 1641 - Picolo Alert PCIe</li> </ul>
Optional accessories	1203 - VEB



## AMERICA

### **Euresys Inc.**

27126-B Paseo Espada - Suite 704  
San Juan Capistrano, CA 92675 - United States

Phone: +1 949 743 0612

Email: [sales.americas@euresys.com](mailto:sales.americas@euresys.com)

## EMEA

### **Euresys SA**

Liège Science Park - Avenue du Pré Aily, 14  
4031 Angleur - Belgium

Phone: +32 4 367 72 88

Email: [sales.europe@euresys.com](mailto:sales.europe@euresys.com)

## EMEA

### **Sensor to Image GmbH**

Lechtorstrasse 20 -  
86956 Schongau - Germany

Phone: +49 8861 2369 0

Email: [sales.europe@euresys.com](mailto:sales.europe@euresys.com)

## ASIA

### **Euresys Pte. Ltd.**

750A Chai Chee Road - #07-15 Viva Business Park  
Singapore 469001 - Singapore

Phone: +65 6445 4800

Email: [sales.asia@euresys.com](mailto:sales.asia@euresys.com)

## CHINA

### **Euresys Shanghai Liaison Office**

Unit 802, Tower B, Greenland The Center - No.500 Yunjin Road, Xuhui District  
200232 Shanghai - China

Euresys上海联络处

上海市徐汇区云锦路500号绿地汇中心B座802室  
200232

Phone: +86 21 33686220

Email: [sales.china@euresys.com](mailto:sales.china@euresys.com)

## JAPAN

### **Euresys Japan K.K.**

Expert Office Shinyokohama - Nisso Dai 18 Building, Shinyokohama 3-7-18  
Kouhoku-Ku, Yokohama-Shi 222-0033 - Japan

〒222-0033

神奈川県横浜市港北区新横浜3-7-18 日総第18ビル エキスパートオフィス新横浜

Phone: +81 45 594 7259

Email: [sales.japan@euresys.com](mailto:sales.japan@euresys.com)

More at [www.euresys.com](http://www.euresys.com)

